

Avaya CM DECT R4 IPBS and Konftel 300Wx

Create Station

On Communication Manger perform the following steps:

- Add Station with the following items set:
 - Type = XMOBILE
 - XMOBILE Type = IPDECT
 - Display Module = y (For MSA this is a check mark)
 - Mobility Trunk Group = <The trunk for the DECT Master at the site>, e.g. 6
 - Cell Phone Number = <same as station extension>
 - Mapping Mode = both
 - Message Lamp Ext = <same as mailbox extension>
 - Message Waiting Type = ICON
 - Length Of Display = 16x2

Create 3725/300Wx DECT User

On Avaya DECT R4 LDAP Database Server (DECT Master) e.g. Internet Explorer 172.1.1.1 login as user = <your user ID>, password = <your password>

- Select Users
- Select New
- Set Long Name = "<set as extension>" e.g. "11002000"
- Set Display Name = "<set as name>" e.g. "Smith, Fred"
- Set Number = "<set as extension>", e.g. "11002000"
- Set Auth Code = <blank>
- Select OK

Subscribe 300Wx DECT phone to IPBS

On the DECT Handset perform the following steps:

- Press the "Menu" key.
- Push the "down" key to navigate to "SETTINGS".
- Push the "OK" key to select "SETTINGS".
- Push the "OK" key to select "DECT".
- Push the "down" key to navigate to "REGISTER".
- Push the "OK" key to select "REGISTER".
- Push the "OK" key to select "BASE 1".
- When prompted for "ENTER PIN CODE", enter the Avaya DECT R4 Authorization Code e.g. 1234567 and push "OK"
- Push the "MENU" key to exit the menu.

Register 3725/300Wx DECT phone to DECT User

On the DECT Handset perform the following steps:

- Dial *<master ID>*<extension>*<AC>#
Example: Dial *0*11002012*1234567#
Master ID is specified by the Avaya DECT R4 administrator, and unique for each coverage zone
- Press green dial button
- Request backup of database server